



# Performance Analysis of the Tesla Model 3 Electric Motor using MotorXP-PM

Part 1

**JUNE 2020** 





## About MotorXP-PM

MotorXP-PM is a powerful software for design and analysis of modern permanent magnet (PM) machines including brushless DC (BLDC), surface-mount (SPM) and interior magnet (IPM) motors.

The software is built from ground up to address the modern PM motor design challenges as well as the motor drive aspect which is tightly linked to the high-performance motor control requirements. For more information, please visit <u>http://motorxp.com</u>.

In this whitepaper, a Tesla Model 3 (2018) rear drive electric motor is used as an example to highlight some of the MotorXP-PM capabilities.

This experimental study is organized into two parts: In part one (this article) exploratory research and high level conclusions are presented; In a follow up part 2 of the series, the detailed use of motorXP software during the study is presented as a tutorial.



#### About Tesla Model 3 IPM motor

Figure 1: Tesla Model 3 Rear Motor Drive [source, tesla.com]

The subject motor is employed in the Tesla Model 3 rear drive unit. The published data suggests the single drive system delivers 190-211kW and 420-450Nm at its peak [2][3].

This experimental study focuses on the accuracy of MotorXP-PM software when it comes to the characteristics and performance analysis of the electric motor. Both public data and experiment data were used for the comparisons and analysis. The study was carried out independently and the result is published here for references only.







### Construction

The subject of the study was acquired from a used vehicle part market marked as 2018 model year long range version. To reconstruct the motor geometry to be imported to the MotorXP software, a tear-down was performed to separate the motor components from the rest of the drive system.



Figure 2: Tesla Model 3 Rear Drive Unit

The motor has been since further separated to reveal the stator and rotor assemblies.



Figure 3: Stator Assembly









With proper tools, the geometry of the stator is then exported to DXF file (with cooling features around the outer perimeter reasonably simplified) and the stator parameters are tabulated as below.

Number of stator slots	54
Stator lamination outer diameter	225 mm
Stator lamination inner diameter	151.3 mm
Lamination stack length	134 mm
Lamination stacking factor (estimated)	0.95

Table 1: Parameters for stator lamination stack

The following parameters were measured from the motor with proper instruments.

End winding axial overhang	40 mm
Number of phases	3
Parallel paths	3
Number of turns	2
Phase resistance at 20°C	0.00475 Ω
Number of pole pairs	3

Table 2: Parameters measured from motor

The rotor subassembly of the Tesla Model 3 electric motor is shown in Figure 4.



Figure 4: Rotor Assembly





Further tear down reveals the lamination.



Figure 5: Rotor Lamination and Magnet

The following parameters were measured from the rotor lamination sheet and the magnet. A DXF file then is derived for later steps. It is interesting to mention that the 4 segments in the magnet does NOT form a Halbach array; Both sides of the magnet measured the same magnetic field evenly. The segmentation of the magnet helps reduce the eddy current thus self-heating of the magnet themselves.

Rotor lamination outer diameter	149.9 mm
Rotor lamination inner diameter	70 mm
Magnet dimension	33x21.5x6.5mm



Figure 6: Combined DXF of the Stator & Rotor Geometry







# **Project Setup**

The DXF files obtained during the teardown are then imported in the MotorXP Design Studio. The winding information, rotor skew information is manually put in to complete the problem setup. The complete procedure will be presented in the part 2 of the white paper series.



# **No Load Characteristics Measurement**

Without proper signal setup it is not possible to perform the full dyno test on the motor using its original motor drive. However some characters of the motor, like the back emf constant, can be derived from the no load tests to determine winding patterns and the materials for laminations and magnets.

The back EMF of the motor was measured by spinning the motor using a third-party motor drive in open-loop mode. The measurements were performed at 222 RMP with magnet at room temperature of 20°C. The measured peak of line-to-line back EMF is determined to be 42 Vp/kRPM.









Figure 8: Measured back EMF waveform at 222 RMP

In Motor XP-PM it is easy to calculate line-to-line back EMF by just subtracting one phase value from another. Figure 9 represents simulated line-to-line back EMF waveform at 1000 rpm. The simulated waveform matches the measurement both in waveform shapes and the peak quantity. This test, in junction with the DC resistance measurements, verifies that the basic information (geometry, winding pattern, material) that were used in the problem setup are close to the actual design.



Figure 9: Simulated line-to-line back-EMF waveform at 1000 rpm







### **Simulation Under Load**

With the back emf and dc resistance verified by the static analysis, further simulations can be carried out with confidence.

To determine the optimal operating point to achieve the peak torque/power of the machine, a DQ analysis was first carried out (see DQ Analysis section) to determine the optimal current and angle to achieve these goals listed in the public data. This operating point is then fed back to the Magnetostatic analysis for more accurate FEA analysis.

Figure 10 shows simulation results for operation with maximum output power and maximum torque according to [1]. Advance angle was adjusted so the maximum torque is produced with minimum possible current of 953 A. The resulting optimum advance angle value is 53.5 electrical degrees.

	Lista				
Desktop About	пер				
🛃 🔒   R 🖉 🎵	〔 🏈 💥 峙 🛝	¥∬ ► =			
Project file name:	tesla_model3_full	oad.mxp			
D-C	Analysis		Finite Element	Analysis	~
Steady State	Dynamic		Magnetostatic	Dynamic	
Magnetostatic Finit	e Flement Analy	sis	-	-	
Solver type:	Nonlinear	010	Convergance tolerance:	0.001	
Solver type.	Nominear •		convergance tolerance.		
Current waveform:	Sinusoidal 🗸		Advance angle:	53.5 <sup>0</sup> (el.de	g.)
Current input method:	RMS supply current	$\sim$	Mechanical speed:	4275 <-rate	d RP
RMS supply current:	953 <-rated	A			
rano supply current.	- Tutou				
Circulation and the					
Simulation setup:	Multiple points (8 point	ts per cogging	) - high accuracy 🗸 🛛 Num	ber of points: 14	14
Simulation setup: Simulation time:	Multiple points (8 point	ts per cogging	) - high accuracy 🗸 Num	ber of points: 14	14
Simulation setup: Simulation time:	Multiple points (8 point One electrical period	ts per cogging	) - high accuracy 🗸 Num	ber of points: 14	14
Simulation setup: Simulation time:	Multiple points (8 point One electrical period rque	ts per cogging	) - high accuracy 🗸 Num	ber of points: 14	14
Simulation setup: Simulation time: Compute cogging to Save each field solu	Multiple points (8 point One electrical period rque Ition	ts per cogging	) - high accuracy 🗸 Num	ber of points: 14	14
Simulation setup: Simulation time: Compute cogging to Save each field solu Results:	Multiple points (8 point One electrical period rque Ition	s per cogging	) - high accuracy 🗸 Num	ber of points: 14	14
Simulation setup: Simulation time: Compute cogging to Save each field solu Results:	Multiple points (8 point One electrical period rque Ition	s per cogging	)-high accuracy 🗸 Num	ber of points: 14	×
Simulation setup: Simulation time: Compute cogging to Save each field solu Results: Rotor speed:	Multiple points (8 point One electrical period rque Ition 4275	RPM	) - high accuracy 💉 Num	eneral Results 70.8549	14 V
Simulation setup: Simulation time: Compute cogging to Save each field solu Results: Rotor speed: Advance angle:	Multiple points (8 point One electrical period rque 4275 53.5	RPM 0 (el.deg.)	) - high accuracy V Num Num RMS phase back-EMF: Input electrical power:	eneral Results 70.8549 211999	14 V W
Simulation setup: Simulation time: Compute cogging to: Save each field solu Results: Rotor speed: Advance angle: Supply frequency:	Multiple points (8 point One electrical period rque tition 4275 53.5 213.75	RPM 0 (el.deg.) Hz	) - high accuracy V Num RMS phase back-EMF: Input electrical power: Output mechanical power:	neral Results 70.8549 211999 192396	14
Simulation setup: Simulation time: Compute cogging to Save each field solu Results: Rotor speed: Advance angle: Supply frequency: RMS phase current:	Multiple points (8 point One electrical period rque 4275 53.5 213.75 953	RPM 0 (el.deg.) Hz A	) - high accuracy V Num RMS phase back-EMF: Input electrical power: Output mechanical power: Efficiency:	neral Results 70.8549 211999 192396 92.1229	14 V W %
Simulation setup: Simulation time: Compute cogging to Save each field solu Results: Rotor speed: Advance angle: Supply frequency: RMS phase current: RMS phase voltage:	Multiple points (8 point One electrical period rque tition 4275 53.5 213.75 953 94.611	RPM 0 (el.deg.) Hz A V	) - high accuracy V Num RMS phase back-EMF: Input electrical power: Output mechanical power: Efficiency: Power factor;	neral Results 70.8549 211999 192396 92.1229 0.770356	14 V W W %
Simulation setup: Simulation time: Compute cogging to Save each field solu Results: Rotor speed: Advance angle: Supply frequency: RMS phase voltage: Total torque:	Multiple points (8 point One electrical period rque 4275 53.5 213.75 953 94.611 429.765	RPM 0 (el.deg.) Hz A V N-m	) - high accuracy V Num RMS phase back-EMF: Input electrical power: Output mechanical power: Efficiency: Power factor: Stator winding loss:	neral Results 70.8549 211999 192396 92.1229 0.770356 15580.1	V W %
Simulation setup: Simulation time: Compute cogging to: Save each field solu Results: Rotor speed: Advance angle: Supply frequency: RMS phase current: RMS phase voltage: Total torque:	Multiple points (8 point One electrical period rque tition 4275 53.5 213.75 953 94.611 429.765 206.738	RPM <sup>0</sup> (el.deg.) Hz A V N-m N-m	) - high accuracy V Num RMS phase back-EMF: Input electrical power: Output mechanical power: Efficiency: Power factor: Stator winding loss: Total iron core loss:	neral Results 70.8549 211999 192396 92.1229 0.770356 15980.1 455.444	14 V W W %
Simulation setup: Simulation time: Compute cogging to Save each field solu Results: Rotor speed: Advance angle: Supply frequency: RMS phase current: RMS phase voltage: Total torque: Reluctance torque: Magnet torque:	Multiple points (8 point One electrical period rque ttion 4275 53.5 213.75 953 94.611 429.765 206.738 223.027	RPM (el.deg.) Hz A V N·m N·m	) - high accuracy V Num RMS phase back-EMF: Input electrical power: Output mechanical power: Efficiency: Power factor: Stator winding loss: Total iron core loss: Eddy current iron core loss:	neral Results 70.8549 211999 192396 92.1229 0.770356 15980.1 15980.1 15980.44 137.449	V W W % W
Simulation setup: Simulation time: Compute cogging to Save each field solu Results: Rotor speed: Advance angle: Supply frequency: RMS phase current: RMS phase current: RMS phase current: RMS phase current: RMS phase current: RMS phase current: Total torque: Magnet torque: Torque ripple:	Multiple points (8 point One electrical period rque ttion 4275 53.5 213.75 953 94.611 429.765 206.738 223.027 6.73589	RPM <sup>0</sup> (el.deg.) HZ N-m N-m 96	) - high accuracy V Num RMS phase back-EMF: Input electrical power: Output mechanical power: Efficiency: Power factor: Stator winding loss: Total iron core loss: Eddy current iron core loss: Hysteresis iron core loss:	neral Results 70.8549 211999 192396 92.1229 0.770356 15980.1 455.444 1317.995	14 V W W W W
Simulation setup: Simulation time: Compute cogging to Save each field solu Results: Rotor speed: Advance angle: Supply frequency: RMS phase voltage: Total torque: Reluctance torque: Magnet torque: Torque ripple: RMS current density:	Multiple points (8 point One electrical period rque tition 4275 53.5 213.75 953 94.611 429.765 206.738 223.027 6.73589 43.8515	RPM (el.deg.) Hz N·m N·m % A/mm <sup>2</sup>	) - high accuracy V Num RMS phase back-EMF: Input electrical power: Output mechanical power: Efficiency: Power factor: Stator winding loss: Total iron core loss: Eddy current iron core loss Hysteresis iron core loss Hysteresis iron core loss	Ineral Results 70.8549 211999 192396 92.1229 0.770356 15980.1 455.444 137.499 317.995 15.8832	
Simulation setup: Simulation time: Compute cogging to: Save each field solu Results: Rotor speed: Advance angle: Supply frequency: RMS phase current: RMS phase voltage: Total torque: Reluctance torque: Magnet torque: Torque ripple: RMS current density: Average d-axis current	Multiple points (8 point One electrical period rque ttion 4275 53.5 213.75 953 94.611 429.765 206.738 223.027 6.73889 4.38515 43.8515 -1083.39	RPM <sup>0</sup> (el.deg.) Hz A V.m N·m N·m % A/mm <sup>2</sup> A	) - high accuracy V Num RMS phase back-EMF: Input electrical power: Output mechanical power: Efficiency: Power factor: Stator winding loss: Total iron core loss: Eddy current iron core loss: Eddy current iron core loss: Magnet eddy current loss: Other eddy current loss:	Provide         Provide <t< td=""><td>44</td></t<>	44
Simulation setup: Simulation time: Compute cogging to: Save each field solu Results: Rotor speed: Advance angle: Supply frequency: RMS phase current: RMS phase voltage: Total torque: Reluctance torque: Magnet torque: Torque ripple: RMS current density: Average d-axis current Average d-axis current	Multiple points (8 point One electrical period rque tition 4275 53.5 213.75 953 94.611 429.765 206.738 223.027 6.73589 43.8515 -1083.39 nt. 80167	RPM 0 (el.deg.) Hz A V N·m N·m N.m % A/mm <sup>2</sup> A	) - high accuracy V Num Ge RMS phase back-EMF: Input electrical power: Output mechanical power: Efficiency: Power factor: Stator winding loss: Total iron core loss: Eddy current iron core loss: Hysteresis iron core loss: Max deman field: Max deman field:	Ineral Results         70.8549         211999           192396         92.1229         0.770356         15580.1           1558.0.1         137.449         317.995         15.6832         0           774404         1449         15.6832         0         15.6832         0	44
Simulation setup: Simulation time: Compute cogging to Save each field solu Results: Rotor speed: Advance angle: Supply frequency: RMS phase current: RMS phase voltage: Total torque: Reluctance torque: Magnet torque: Torque ripple: RMS current density: Average d-axis current Average d-axis current	Multiple points (8 point One electrical period rque ttion 4275 53.5 213.75 953 94.611 429.765 206.735 206.735 89 43.8515 -1083.39 att. -1083.39 att. -1083.39	RPM <sup>0</sup> (el.deg.) HZ A V N·m N·m S A/mm <sup>2</sup> A V	) - high accuracy V Num Ge RMS phase back-EMF: Input electrical power: Output mechanical power: Output mechanical power: Efficiency: Power factor: Stator winding loss: Total iron core loss: Eddy current iron core loss: Magnet eddy current loss: Other eddy current loss: Other eddy current loss: Max. demag. field: Max. demag. field:	Total Results         Total Results           70.8549         211999           192396         92.1229           0.770356         15980.1           455.444         317.995           15.6832         0           7774404         774404           19.2889         12889	44

Figure 10: Magnetostatic Analysis setup and simulation results of Tesla Model 3 motor for operation with maximum output power and maximum torque

This simulation verifies the published data on [2][3] about the peak power and peak torque to a very close proximity. The predicted 430Nm and 192kW can be achieved at close to





1000Arms phase current under 94.61V of RMS voltage, which translates to 231Vdc minimum bus voltage.

#### Magnetostatic Analysis

Most of the characters of the motor can be determined by fast Magnetostatic analysis for a first principle examination. Besides the torque, voltage, current and loss information, some underlying quantities can be extracted from this type of analysis too. For example, the flux density distribution plot is calculated to make sure that the motor is not saturated during operation. Figure 11 represents the flux density distribution. It aims to study the flux distribution at different parts of the motor and to predict safety and efficiency of the motor by increasing torque and current accordingly.



Figure 11: Flux density distribution of Tesla Model 3 motor for operation with maximum output power and maximum torque





## **DQ** Analysis

DQ models are used widely by control engineers for algorithm design and stability analysis. One of the distinguishing features of the MotorXP is the capability to map out the full DQ parameter spectrum across the full operational range. By building the DQ parameter map once using the highly accurate FEA engine, it would allow the easy generation of the efficiency maps and variety of operational charts and envelopes at any operating points with superior accuracy. Control engineers can also export the DQ parameters or Id / Iq tables to easily build control algorithms with maximum torque per amp or max efficiency at each operation point.

Some exemplary charts are presented below.













#### **Dynamic Finite Element Analysis**

Dynamic FEA option provides the most accurate details of the machine simulation. It provides the extra accuracy (comparing to magnetostatic analysis) by considering the dynamic terms in the Maxwell equations.



Figure 14: Example of Dynamic FEA results – radial force and airgap mmf

#### Summary

In this first part of the 2-part series of the Tesla Model 3 rear motor analysis using MotorXP-PM, high level capability of the software is demonstrated by comparing the simulated results with the available motor data from publication and measurements. Some simulation results are presented as an example to predict the operational envelope of the model 3 drive system.

The project used in this whitepaper is available as a part of examples in the MotorXP-PM software package. A trial version of the software can be requested from <a href="https://motorxp.com/downloads/">https://motorxp.com/downloads/</a>.







#### References

[1]. MOTORTREND - 2018 Tesla Model 3 Dual Motor Performance Quick Test Review. https://www.motortrend.com/cars/tesla/model-3/2018/2018-tesla-model-3-dual-motorperformance-quick-test-review/

[2]. New Tesla Model 3 details revealed by EPA: ~80 kWh battery pack, 258 hp, and more. <u>https://electrek.co/2017/08/07/tesla-model-3-new-details-revealed/#jp-carousel-49431</u>

[3]. Wikipedia https://en.wikipedia.org/wiki/Tesla\_Model\_3





